COUGAR

ALLIED ELECTRONICS

4 Channel Car Power Amplifier

C600-4

BRIDGEABLE

4 Channel Car Power Amplifier
4x500W max. at 4 Ohm power amplifier
4x125W RMS at 4 Ohm ± 0,5% THD
2x 300W RMS bridged connected at 4 Ohm ± 5% THD
Mosfet amplifier technology
Dual integrated switched power supply
Bridgeable final amplifier

Frequency responce	: 10Hz ~ 40kHz ± 3dB
Input sensitivity	: 230mV to 6V (low/hi)
Input impedance	: 47K Ohm
Signal/noise	: >97dB
Output impedance	: 2 ~ 8 Ohm (stereo)
Output impedance	: 4 ~ 8 Ohm (mono)
Power supply	: DC10V ~ DC14V (40 Ampère)
Low pass filter	: 50Hz ~ 250Hz
High pass filter	: 120Hz ~ 3kHz
Bass boost switch	: 0dB ~ 6dB

Built-in power security circuit with indication LED
Double separated 15A fuse
Stereo RCA line output
Dimensions: 294 x 265 x 55 (mm)(lxwxh)

Weight	: 1,7 Kg
Qty/ctn	: 5
Barcode	: 5400784037363

HIGH POWER MOSFET